



DIGIT S2 e

DigitalSat-Receiver mit integriertem Conax-Entschlüsselungssystem

EAN	Colour	Item no.	Weight (Box)	Weight	Device (W x H x D)	Box
4019588316676	silver	0031/4667	900 g	400 g	21 x 3,6 x 13 cm	32,5 x 5,5 x 23,3 cm

TOP FEATURES

Kompaktes Gehäuse

Integriertes Conax-Entschlüsselungssystem

SIM-Card Reader

DigiButler Service ("SiehFern INFO", ISIPRO, TechniMatic, AutoInstall)

AMBIENT OPERATING CONDITIONS

Ambient temperature: 5 ... 35 °C

Humidity: 10 ... 75 %

LNB CONTROL

Vertical: 14 V

Horizontal: 18 V

Band switch: 22 kHz

Current consumption: max. 400 mA
(kurzschlussfest)

DiSEqC: 1.0 / 1.2 / Sat-CR

TECHNISAT ADDED VALUE SERVICES

AUTOINSTALL: Yes

CONNECTIONS

SIM-Card reader: Yes

Digital electric audio output (S/PDIF): Yes

Audio out analogue (RCA): Yes (rechts / links)

Scart: 2

F socket: 1

RS-232: 1

DECRYPTION SYSTEM

Conax: Yes

DISPLAY

Freeze frame: Yes

Zoom: Yes

SD: Yes

576i: Yes

HANDLING/COMFORT

Clock: Yes

Sleep timer: Yes

OTHER FEATURES

OSD languages: English, German, French, Italian,
Dutch, Polish, Spanish, Czech, Turkish,
Hungarian

Total programme memory: 4.000

POWER CONSUMPTION

Standby fast start: 2,48 W

Standby LED: 0,23 W

In operation: < 8 W

POWER SUPPLY

Nominal voltage: 230 V

Frequency: 50 Hz

Mains adapter: internal

TUNER

Tuner type: DigitalSat

DVB-S tuner: 1

Reception on: SD (MPEG-2)

Input impedance: 75 Ω

TECHNIROUTER ready: Yes

TUNER - SAT

FEC: Viterbi and Reed-Solomon

Reception range: 950 ... 2.150 MHz

Viterbi rates: 1/2, 2/3, 3/4, 5/6, 7/8 , (autom. Anpassung)

DVB-S: Shaped QPSK

DVB-S: 2 ... 45

SCOPE OF DELIVERY

DIGIT S2 e, Remote control with batteries, Power cable, Instruction manual, Warranty card