

DIGITRADIO 210 IR HIT Edition

Portable digital radio to receive DAB+, VHF and internet radio via direct dialing buttons to receive radio B2, radio GOLD and STAR*SAT Radio via internet

Colour	EAN	Item no.	Weight (Box)	Weight	Device (W x H x D)	Box
weiß/schwarz	4019588110014	0011/4961	478 g	546 g	23 x 11,5 x 5,3 cm	29 x 12,5 x 6,5 cm

TOP FEATURES

- DAB frequency: 174 - 240 MHz
- RDS PLL UHF radio
- favorite store for up to 10 channels DAB+ and 10 channels UKW
- Date and time display
- Illuminated dot matrix LCD display
- In-built (LiPo) battery with up to 10 hours' life
- 3 direct dialing buttons for radio B2, radio GOLD und STAR*SAT Radio
- Embedded wi-fi connectivity
- Over 11,000 well arranged internet radio stations

HANDLING/COMFORT

- Favourites programme manager DAB+: 10
- Favourites programme manager FM: 10

POWER CONSUMPTION

- Standby: 1 W

CONNECTIONS

- Headphone connection jack (3,5 mm): 1

LOUDSPEAKERS

- Output performance: 1 W (RMS)

AMBIENT OPERATING CONDITIONS

- Humidity: 5 - 90 % relative Luftfeuchtigkeit (nicht kondensierend)
- Ambient temperature: 5 - 35 °C

WLAN

- WLAN: 802.11 a/b/g/n (2,4-GHz- und 5-GHz-Band werden unterstützt)

OTHER FEATURES

- OSD languages: English, German, French, Polish, Italian, Dutch, Norwegian, Danish, Swedish, Finnish, Spanish, Portuguese

ONE-TOUCH BUTTON

- radio GOLD: Yes
- radio B2: Yes
- STAR*SAT: Yes

DISPLAY

- Resolution (vertical and horizontal): 31,3 x 19
- Type: LCD

RADIO / RECEPTION
DAB+: 174 - 240 MHz
FM/RDS: 87,5 - 108 MHz
Internet radio: Yes
Aerial: DAB / UHF telescopic aerial

POWER SUPPLY
Nominal voltage: 230 V
Frequency: 50 Hz
Mains adapter: DC 6 V / 500 mA
Type of power supply: Extern

SCOPE OF DELIVERY
DigitRadio 210, plug-in power supply, instruction manual