



DIGITRADIO 120 IR

DAB+ and FM radio receiver with internet radio, multiroom streaming and Spotify Connect

EAN	Item no.	Colour
4019588970052	0000/4975	black/silver

TOP FEATURES

DAB+ digital radio

RDS UKW radio

Internet radio via WiFi

Compatible with Spotify Connect

3,2" TFT display

Music playback home network via DLNA/UPnP

Bluetooth audio streaming (reception)

Multiroom streaming

Controlable via MyDigitRadio App-Pro (iOS/Android)

Remote control

WLAN

WLAN: 802.11 a/b/g/n (2,4-GHz- und 5-GHz-Band werden unterstützt)

AMBIENT OPERATING CONDITIONS

Humidity: 5 - 90 % relative Luftfeuchtigkeit (nicht kondensierend)

Ambient temperature: 5 - 35 °C

BLUETOOTH VERSION & PROFILE

Bluetooth version: 4

AVRCP (Audio Video Remote Control Profile): ja

A2DP (Advanced Audio Distribution Profile): ja

HFP (Hands Free Profile): ja

HSP (Headset Profile): ja

CONNECTIONS

Digital optical audio out: Yes (SPDIF)

Audio out analogue (3,5 mm jack): 1

connector external antenna: 1

DISPLAY

Size: 3,2 in

Resolution (vertical and horizontal): 240 x 320

RadioVIS: Yes

Dimmable: Yes

Slide show/catSLS: Yes

Type: TFT-Farbdisplay

HANDLING/COMFORT

Alarm: Yes

Sleep timer: Yes

Snooze: Yes

Favourites programme manager DAB+: 10

Favourites programme manager FM: 10

OTHER FEATURES

OSD languages: English, German, French, Polish, Italian, Dutch, Norwegian, Danish, Swedish, Finnish, Spanish, Portuguese

POWER CONSUMPTION

Power consumption in standby mode with active network connection: 1,67 W

In operation: 3 W

Standby: 0,68 W

POWER SUPPLY

Nominal voltage: 230 V

Frequency: 50 Hz

Mains adapter: DC 6 V / 500 mA

Type of power supply: Extern

RADIO / RECEPTION

DAB+: 174 - 240 MHz

FM/RDS: 87,5 - 108 MHz

Internet radio: Yes

Aerial: DAB/FM aerial

STREAMING

Spotify: Yes

Bluetooth audio streaming: Yes

Audio streaming: Yes

SCOPE OF DELIVERY

DigitRadio 120 IR, DAB / FM wire antenna, power supply, remote control, user manual