

DIGITRADIO 51

DAB+/FM clock radio with two independent easy set alarms

EAN	Item no.	Colour	Weight (Box)	Weight	Device (W x H x D)	Box
4019588100084	0000/4981	anthracite	650 g	436 g	14,9 x 4,9 x 12,6 cm	24,5 x 6,8 x 13,7 cm
4019588800014	0001/4981	white	648 g	436 g	14,9 x 4,9 x 12,6 cm	24,5 x 6,8 x 13,7 cm

TOP FEATURES

- DAB+ digital radio
- RDS-PLL VHF radio
- Station memory (2 DAB+/2 VHF)
- Date and time display
- Two wake-up times adjustable
- Alarm via acoustic signal or radio station
- Adjustable alarm frequency
- Snooze and sleeptimer functions
- Large LCD display with illumination and separate time display

FILTER-NAVIGATION

- Features: Alarm clock
- Operating mode: Mains operation
- Connections: Headphone jack (3.5 mm)
- Reception type: FM

AMBIENT OPERATING CONDITIONS

- Humidity: 5 - 90 % relative air humidity (non-condensing)
- Ambient temperature: 5 - 35 °C

CONNECTIONS

- Headphone connection jack (3,5 mm): 1

DISPLAY

- Type: LCD
- Size: 4,5 in
- Dimmable: Yes

HANDLING/COMFORT

- Clock: Yes
- Automatic time reset following a power cut: Yes
- Alarm: Yes
- Sleep timer: Yes
- Snooze: Yes
- Favourites programme manager FM: 2
- Favourites programme manager DAB+: 2

LOUDSPEAKERS

- Output performance: 1,5 W (RMS)
- Mono speakers: Yes

OTHER FEATURES

OSD languages: English, German, French, Italian, Danish, Spanish

POWER CONSUMPTION

Standby: 0,44 W

In operation: 3 W

POWER SUPPLY

Nominal voltage: 230 V

Frequency: 50 Hz

Mains adapter: DC 6 V / 500 mA

Type of power supply: external

RADIO / RECEPTION

DAB+: 174 - 240 MHz

FM/RDS: 87,5 - 108 MHz

Aerial: DAB/FM aerial

SCOPE OF DELIVERY

DigitRadio 51, Power Supply, Instruction Manual