



DIGITRADIO 51

DAB+/FM clock radio with two independent easy set alarms

EAN	Item no.	Colour	Weight (Box)	Weight	Device (W x H x D)	Box
4019588100084	0000/4981	anthracite	650 g	436 g	14,9 x 4,9 x 12,6 cm	24,5 x 6,8 x 13,7 cm
4019588800014	0001/4981	white	648 g	436 g	14,9 x 4,9 x 12,6 cm	24,5 x 6,8 x 13,7 cm

TOP FEATURES

DAB+ digital radio

Date and time display

Adjustable alarm frequency

RDS-PLL VHF radio

Two wake-up times adjustable

Snooze and sleeptimer functions

Station memory (2 DAB+/2 VHF)

Alarm via acoustic signal or radio station

Large LCD display with illumination and separate time display

FILTER-NAVIGATION

Features: Alarm clock

Operating mode: Mains operation

Connections: Headphone jack (3.5 mm)

Reception type: FM

AMBIENT OPERATING CONDITIONS

Humidity: 5 - 90 % relative air humidity (non-condensing)

Ambient temperature: 5 - 35 °C

CONNECTIONS

Headphone connection jack (3,5 mm): 1

DISPLAY

Type: LCD

Size: 4,5 in

Dimmable: Yes

HANDLING/COMFORT

Clock: Yes

Automatic time reset following a power cut: Yes

Alarm: Yes

Sleep timer: Yes

Snooze: Yes

Favourites programme manager FM: 2

Favourites programme manager DAB+: 2

LOUDSPEAKERS

Output performance: 1,5 W (RMS)

Mono speakers: Yes

OTHER FEATURES

OSD languages: English, German, French, Italian, Danish, Spanish

POWER CONSUMPTION

Standby: 0,44 W

In operation: 3 W

POWER SUPPLY

Nominal voltage: 230 V

Frequency: 50 Hz

Mains adapter: DC 6 V / 500 mA

Type of power supply: external

RADIO / RECEPTION

DAB+: 174 - 240 MHz

FM/RDS: 87,5 - 108 MHz

Aerial: DAB/FM aerial

SCOPE OF DELIVERY

DigitRadio 51, Power Supply, Instruction Manual