



DIGITRADIO UP 55

Set with flush-mounted radio and flush-mounted speaker

EAN	Colour	Item no.	Weight (Box)	Weight	Device (W x H x D)	Box
4019588139015	white	0001/3901	370 g	170 g	7 x 7 x 4 cm	19,5 x 6,3 x 11 cm

TOP FEATURES

- Compact digital radio: The flush-mounted radio consists of two units. Radio and speaker can be installed flexibly, e.g. in a double flush-mounted box, either vertically or horizontally
- Flexible: The radio is delivered without a cover frame, both inserts are 55 mm high and wide. They can be combined with standard cover frames from well-known switch program manufacturers
- Features: The digital radio with sleep and alarm timer receives analog and digital radio stations and also allows wireless music streaming via Bluetooth
- Display/Operation: The OLED display shows station names and has a dimming function. Additionally, 20 DAB Plus and FM stations can be saved as favorites
- Good to know and not a defect: Turn off power circuit before installation and only turn it back on after installing the radio and attaching the display, otherwise no display will appear

SONSTIGES

abmasse_stationaer: Yes ,geeignet für Standardrahmen mit 55x55 mm

abmasse_portabel: No

bf_filter_operating_mode: Mains operation

bf_filter_austattung: Bluetooth

bed_schutzklasse: IP 20

radio_typ_unterputzradio: Ja

AMBIENT OPERATING CONDITIONS

Humidity: 10 - 75 % relative air humidity (non-condensing)

Ambient temperature: 5 - 35 °C

BLUETOOTH VERSION & PROFILE

Bluetooth version: 5

AVRCP (Audio Video Remote Control Profile): Yes

A2DP (Advanced Audio Distribution Profile): Yes

DISPLAY

Type: OLED

Resolution (vertical and horizontal): 128x64

Dimmable: Yes

GENERAL CHARACTERISTICS

Colour: Front: RAL 9016, part: RAL 9010

HANDLING/COMFORT

Alarm: Yes

Sleep timer: Yes

Favourites programme manager DAB+: 20

Favourites programme manager FM: 20

LOUDSPEAKERS	NETWORK & COMMUNICATION	POWER CONSUMPTION	
Output performance: 2x 2 W (RMS) for optional 2nd speaker	Bluetooth: Yes	Standby: 0,5 W	
Mono speakers: Yes		Power consumption in standby mode with active network connection: 0,5 W	
Equalizer: Yes		In operation: 6 W max.	
POWER SUPPLY	RADIO / RECEPTION	RADIO TYPE	SCOPE OF DELIVERY
Nominal voltage: 230 V	DAB+: 174 - 240 MHz	stationary radio: Yes	1x flush-mounting radio, 1x flush-mounting speaker with speaker cable (24 cm long), instruction manual
Frequency: 50 Hz	FM/RDS: 87,5 - 108 MHz		
	Aerial: DAB / FM cable antenna		