



DIGITRADIO 303 SWR3 Edition

DAB+/UKW/Internet-Radio mit SWR3 Direktwahltaste

EAN	Colour	Item no.	Weight (Box)	Weight	Device (W x H x D)	Box
4019588039087	black	0000/3908	1,54 kg	1 kg	20,7 x 12,3 x 11,2 cm	26,6 x 22,2 x 18 cm

TOP FEATURES

DAB+ digital radio

RDS-PLL FM radio

Boundless music diversity via Internet radio

2.4" TFT colour display

Station memory (10 DAB+/10 FM)

Integrated wi-fi connectivity

UPnP client in the home network (audio streaming)

Bluetooth audio streaming (reception)

Memory key for SWR3 via DAB+ or internet

Alarm functions

WLAN

WLAN: 802.11 a / b / g / n (2.4 GHz and 5 GHz band supported)

AMBIENT OPERATING CONDITIONS

Humidity: 5 - 90 % relative Luftfeuchtigkeit (nicht kondensierend)

Ambient temperature: 5 - 35 °C

BLUETOOTH VERSION & PROFILE

Bluetooth version: 2.1+EDR

AVRCP (Audio Video Remote Control Profile): ja

A2DP (Advanced Audio Distribution Profile): ja

CONNECTIONS

Headphone connection jack (3,5 mm): 1

DISPLAY

Size: 2,4 in

Resolution (vertical and horizontal): 240x320

RadioVIS: Yes

Type: LCD

Slide show/catSLS: Yes

Dimmable: Yes

HANDLING/COMFORT

Clock: Yes

Alarm: Yes

Sleep timer: Yes

Snooze: Yes

Favourites programme manager FM: 10

Favourites programme manager DAB+: 10

LOUDSPEAKERS

Mono speakers: Yes

Output performance: 2 W (RMS)

OTHER FEATURES

OSD languages: English, German, French, Italian, Norwegian, Danish, Swedish

RADIO / RECEPTION

DAB+: 174 - 240 MHz

FM/RDS: 87,5 - 108 MHz

Internet radio: Yes

Aerial: DAB / FM telescopic aerial

TECHNISAT CONNECT

Control: Yes

NETWORK & COMMUNICATION

Bluetooth: Yes

POWER CONSUMPTION

Power consumption in standby mode with active network connection: < 2 W

In operation: 9 W

Standby: < 1 W

STREAMING

Bluetooth audio streaming: Yes

Audio streaming: Yes

ONE-TOUCH BUTTON

SWR3: Yes

POWER SUPPLY

Nominal voltage: 230 V

Frequency: 50 Hz

Mains adapter: DC 9 V / 1000 mA

Type of power supply: external

SUPPORTED FORMATS & CODECS

Audio-Formats: AAC, MP3, WMA

SCOPE OF DELIVERY

DIGITRADIO 303 SWR3 Edition, mains adapter, manual