



Scene switch 1

4 buttons remote control

Colour	EAN	Item no.	Weight (Box)	Weight	Device (W x H x D)	Box
white	4019588502093	0000/9521	60 g	26 g	5 x 5 x 1,5 cm	8 x 8 x 3 cm

TOP FEATURES

TechniSat smart home component

Integration via TechniSat CONNECT-App

Remote control with 4 buttons

Control 8 different scenes - Press and hold for each button

Installation on the wall or use as portable remote control

Power supply: rechargeable batterie or USB micro 5V

Z-Wave™ wireless sensor (868.42 MHz)

FILTER-NAVIGATION

Operating mode: Rechargeable battery

AMBIENT OPERATING CONDITIONS

IP class: 20

Ambient temperature: 0 ... 40 °C

Humidity: 10 - 75 %

CONNECTIONS

USB charging: Yes

FUNK COMMUNICATION

Telecommunication: Z-Wave Plus

Range inside: max. 40 m

Range outside: max. 100 m

operating frequency: 868,42 MHz

POWER SUPPLY

Nominal voltage: 3,6 V

Battery charge via USB: Yes

Battery life: bis zu 6 months

Rechargeable battery: Li-Ion LIR2450

SCOPE OF DELIVERY

Szenenschalter 1, batterie LIR2450,USB charging cable, double-sided mounting tape, manual