



## DIGITRADIO 52 CD

DAB+ / FM clock radio with CD player, Bluetooth audio streaming and wireless charging function

Colour	EAN	Item no.	Weight (Box)	Weight	Device (W x H x D)	Box
white	4019588139398	0001/3939	1,94 kg	1,42 kg	18 x 12,5 x 20 cm	24 x 20,5 x 23 cm
anthracite	4019588039391	0000/3939	1,94 kg	1,42 kg	18 x 12,5 x 20 cm	24 x 20,5 x 23 cm

### TOP FEATURES

DAB+ digital radio

FM radio (with RDS and PLL)

Favourites memory (20 for DAB+ and 20 for FM)

Date and time display

Two radio alarms available

Large LCD display with backlight

Bluetooth audio streaming

CD/MP3 player

Wireless charging for charging smartphones

### SONSTIGES

bf\_filter\_anschuesse: USB

abmasse\_portabel: No

bf\_filter\_austattung: Bluetooth

abmasse\_stationaer: Yes

bf\_filter\_operating\_mode: Mains operation

### AMBIENT OPERATING CONDITIONS

Humidity: 5 - 90 % relative air humidity (non-condensing)

Ambient temperature: 5 - 35 °C

### BLUETOOTH VERSION & PROFILE

Bluetooth version: 4

AVRCP (Audio Video Remote Control Profile): Ja

A2DP (Advanced Audio Distribution Profile): Ja

### CONNECTIONS

Headphone connection jack (3,5 mm): 1

USB: 1

### DISPLAY

Type: LCD

Size: 4,7 in

Dimmable: Yes (automatisch mit Lichtsensor)

### FUNCTIONS

MP3 playback via USB: Yes

USB charging function: Yes

Wireless charging: Yes (compatible with the Qi charging standard)

#### HANDLING/COMFORT

Clock: Yes

Automatic time reset following a power cut: Yes

Alarm: Yes

Sleep timer: Yes

Snooze: Yes

Favourites programme manager FM: 20

Favourites programme manager DAB+: 20

#### OTHER FEATURES

OSD languages: English, German, French, Italian

#### RADIO / RECEPTION

DAB+: 174 - 240 MHz

FM/RDS: 87,5 - 108 MHz

Aerial: DAB/FM dipole antenna

#### SCOPE OF DELIVERY

DIGITRADIO 52 CD, power adapter, instruction manual

#### LOUDSPEAKERS

Output performance: 4 W (RMS)

Stereo speakers: Yes

Stereo: 2 x 2 W

Equalizer: Yes

#### POWER CONSUMPTION

Standby: 1 W

Power consumption in standby mode with active network connection: 1 W

In operation: 15 W max.

#### RADIO TYPE

stationary radio: Yes

#### NETWORK & COMMUNICATION

Bluetooth: Yes

#### POWER SUPPLY

Nominal voltage: 230 V

Frequency: 50 Hz

Mains adapter: DC V / mA

Type of power supply: External

#### STREAMING

Bluetooth audio streaming: Yes