



## DIGITRADIO 10

DAB+ / FM receiver / radio adapter with OLED display and Bluetooth audio streaming

Colour	EAN	Item no.	Weight (Box)	Weight	Device (W x H x D)	Box
schwarz/silber	4019588039445	0000/3944	598 g	142 g	12 x 9 x 6 cm	17,5 x 17,25 x 7,75 cm

### TOP FEATURES

- Tuner module for upgrading existing stereo systems, AV receivers, or active speakers. The digital radio adapter functions solely as a receiver and does not have built-in speakers
- Display brightness can be adjusted for both operation and standby; time, date, station, and title names are shown on the large, easy-to-read OLED display
- Adapter for receiving DAB+ radio, FM, and music playback via Bluetooth. The digital radio can be easily controlled with the included remote control
- The adapter is only usable in conjunction with a hi-fi system, AV receiver, or active speakers – the DIGITRADIO 10 was developed and manufactured in Germany, quality Made in Germany

### SONSTIGES

bf\_filter\_austattung: Bluetooth

abmasse\_portabel: No

bf\_filter\_anschluess: Analog audio input (L/R)

abmasse\_stationaer: Yes

bf\_filter\_operating\_mode: Mains operation

### AMBIENT OPERATING CONDITIONS

Humidity: 5 - 90 % relative air humidity (non-condensing)

Ambient temperature: 5 - 35 °C

### BLUETOOTH VERSION & PROFILE

Bluetooth version: 5

AVRCP (Audio Video Remote Control Profile): Yes

A2DP (Advanced Audio Distribution Profile): Yes

#### CONNECTIONS

Audio out analogue (RCA): Yes

connector external antenna: 1

#### DISPLAY

Type: OLED

Size: 2,4 in

Dimmable: Yes

#### HANDLING/COMFORT

Clock: Yes

Automatic time reset following a power cut: Yes

Alarm: Yes

Sleep timer: Yes

Snooze: Yes

Remote control: Yes

Favourites programme manager FM: 20

Favourites programme manager DAB+: 20

#### NETWORK & COMMUNICATION

Bluetooth: Yes

#### OTHER FEATURES

OSD languages: English, German, French, Italian

#### POWER CONSUMPTION

Standby: 0,47 W

In operation: 1,2 W

#### POWER SUPPLY

Nominal voltage: 230 V

Frequency: 50 Hz

Mains adapter: DC 5 V / 1.000 mA

Type of power supply: External

#### RADIO / RECEPTION

DAB+: 174 - 240 MHz

FM/RDS: 87,5 - 108 MHz

Aerial: DAB/FM dipole antenna

DAB+ cable: 252 - 261 MHz

#### RADIO TYPE

stationary radio: Yes

radio adapter: Yes

#### STREAMING

Bluetooth audio streaming: Yes

#### SCOPE OF DELIVERY

DIGITRADIO 10, DAB / FM aerial antenna, audio connection cable, power adapter, remote control, user manual