



DIGITRADIO 10 C

DAB+ / FM receiver / radio adapter with colour display and Bluetooth audio streaming

Colour	EAN	Item no.	Weight (Box)	Weight	Device (W x H x D)	Box
black/silver	4019588039452	0000/3945	612 g	153 g	12 x 9 x 6 cm	17,5 x 17,25 x 7,75 cm

TOP FEATURES

- Tuner module for upgrading existing stereo systems, AV receivers, or active speakers. The digital radio adapter functions solely as a receiver and does not have built-in speakers
- The adapter is only usable in conjunction with a hi-fi system, soundbar, or active speakers – the DIGITRADIO 10 C was developed and manufactured in Germany, quality Made in Germany
- Adapter with color display for receiving DAB+ radio, FM, and music playback via a Bluetooth connection
- The digital radio can be easily controlled with the included remote. Time, date, station, and track names are displayed on the large, easy-to-read 2.8-inch color display

SONSTIGES

abmasse_stationaer: Yes

bf_filter_operating_mode: Mains operation

bf_filter_aneschluesse: Analog audio input (L/R)

abmasse_portabel: No

bf_filter_austattung: Bluetooth

AMBIENT OPERATING CONDITIONS

Humidity: 5 - 90 % relative air humidity (non-condensing)

Ambient temperature: 5 - 35 °C

BLUETOOTH VERSION & PROFILE

Bluetooth version: 5

AVRCP (Audio Video Remote Control Profile): Yes

A2DP (Advanced Audio Distribution Profile): Yes

CONNECTIONS

Audio out analogue (RCA): Yes

connector external antenna: 1

DISPLAY

Type: TFT colour display

Size: 2,8 in

Resolution (vertical and horizontal): 240 x 320

Dimmable: Yes

Slide show/catSLS: Yes

HANDLING/COMFORT

Clock: Yes

Automatic time reset following a power cut: Yes

Alarm: Yes

Sleep timer: Yes

Snooze: Yes

Remote control: Yes

Favourites programme manager FM: 20

Favourites programme manager DAB+: 20

NETWORK & COMMUNICATION

Bluetooth: Yes

OTHER FEATURES

OSD languages: English, German, French, Polish, Italian, Dutch, Czech, Slovakian, Norwegian, Danish, Swedish, Finnish, Spanish, Turkish, Portuguese

POWER SUPPLY

Nominal voltage: 230 V

Frequency: 50 Hz

Mains adapter: DC 5 V / 1.000 mA

Type of power supply: External

RADIO / RECEPTION

DAB+: 174 - 240 MHz

FM/RDS: 87,5 - 108 MHz

Aerial: DAB/FM dipole antenna

DAB+ cable: 252 - 261 MHz

POWER CONSUMPTION

Standby: 0,64 W

In operation: 1,5 W

RADIO TYPE

stationary radio: Yes

radio adapter: Yes

STREAMING

Bluetooth audio streaming: Yes

SCOPE OF DELIVERY

DIGITRADIO 10 C, DAB/FM dipole antenna, audio connection cable, power supply unit, remote control, instruction manual

Test Results DIGITRADIO 10 C



Note: sehr gut (92,1 %)

SATVISION 11/19