



## DIGIFLEX TT5

Active rod antenna with built-in amplifier for the reception of DVB-T and DAB+

| Colour | EAN           | Item no.  | Weight (Box) | Weight | Device (W x H x D) | Box                 |
|--------|---------------|-----------|--------------|--------|--------------------|---------------------|
| black  | 4019588060258 | 0000/6025 | 230 g        | 152 g  | 7 x 34,5 x 7 cm    | 7,5 x 32,5 x 5,5 cm |

### TOP FEATURES

- Compact active indoor antenna for receiving digital television via DVB-T2 and digital radio via DAB+/FM without an outdoor antenna
- Easy installation via the antenna socket of the receiver and stable placement thanks to the built-in magnet in the antenna base
- Strong reception: The LTE filter eliminates interference from mobile signals and, together with the signal amplifier, ensures strong and stable reception
- The antenna is powered by the connected receiving device – 5 volts (40 mA); Reception range: VHF: 87.5 ... 230 MHz, UHF: 470 ... 790 MHz
- Note: When using with DAB+ receivers, the antenna input of the DAB+ radio must supply 5 V power to the antenna; otherwise, it will not work

### AMPLIFICATION

VHF: 24 dB

UHF: 26 dB

### GENERAL CHARACTERISTICS

Cable length: 2 m

### POWER SUPPLY

Antenna feed: 5V by the receiver

**RECEPTION RANGE**

VHF: 87,5 ... 230 MHz

UHF: 470 ... 790 MHz

**TECHNICAL DATA**

Noise factor: 3,5 dB

Protection class: IP20

Connector type: IEC

Impedance: 75 Ω

**SCOPE OF DELIVERY**

Rod antenna, base with antenna cable and amplifier, Quick Start Guide