



DIGITRADIO 11 IR

Receiver / radio adapter for DAB+ / FM / Internet radio with colour display and Bluetooth audio streaming

Colour	EAN	Item no.	Weight (Box)	Weight	Device (W x H x D)	Box
black/silver	4019588039582	0000/3958	620 g	156 g	12 x 9 x 6 cm	17 x 7,5 x 17 cm

TOP FEATURES

- Compact radio adapter: The receiver is used to upgrade existing stereo systems or AV receivers to receive digital and internet radio – the adapter has no built-in speakers
- Premium features: In addition to DAB+ and internet radio reception, you have access to music services like Spotify, Amazon Music, and more. Experience crystal-clear audio with Bluetooth streaming and built-in Wi-Fi.
- Full flexibility: Additionally, up to 30 FM and DAB stations can be saved. Operation is simple and intuitive using the included remote control or conveniently via app.
- Comfort: The dimmable 3.5-inch color display shows the time, station name, and additional information about the current program. Convenient features include wake timer, sleep timer, and the option to connect an external antenna

SONSTIGES

abmasse_stationaer: Yes

bf_filter_anchluss: Wi-Fi

bf_filter_operating_mode: Mains operation

abmasse_portabel: No

bf_filter_austattung: Bluetooth

WLAN

WLAN: 802.11 a / b / g / n (2.4 GHz and 5 GHz band supported)

AMBIENT OPERATING CONDITIONS

Humidity: 5 - 90 % relative air humidity (non-condensing)

Ambient temperature: 5 - 35 °C

BLUETOOTH VERSION & PROFILE	CONNECTIONS	DISPLAY
Bluetooth version: 5	Digital optical audio out: Yes (SPDIF)	Type: TFT colour display
AVRCP (Audio Video Remote Control Profile): Yes	Audio out analogue (RCA): Yes	Size: 3,5 in
A2DP (Advanced Audio Distribution Profile): Yes	connector external antenna: 1	Resolution (vertical and horizontal): 480x320
		Dimmable: Yes
		Slide show/catSLS: Yes
		RadioVIS: Yes
HANDLING/COMFORT	LOUDSPEAKERS	NETWORK & COMMUNICATION
Clock: Yes	Equalizer: Yes	Bluetooth: Yes
Alarm: Yes		
Sleep timer: Yes		
Snooze: Yes		
Remote control: Yes		
Favourites programme manager FM: 30		
Favourites programme manager DAB+: 30		
OTHER FEATURES	POWER CONSUMPTION	POWER SUPPLY
OSD languages: English, German, French, Polish, Italian, Dutch, Czech, Slovakian, Norwegian, Danish, Spanish, Slovenian, Portuguese, Turkish	Standby: 0,72 W	Nominal voltage: 230 V
	In operation: 1,4 W	Frequency: 50 Hz
		Mains adapter: DC 5 V / 1000 mA
		Type of power supply: External
RADIO / RECEPTION	RADIO TYPE	SCOPE OF DELIVERY
DAB+: 174 - 240 MHz	radio adapter: Yes	DIGITRADIO 11 IR, DAB / FM dipole antenna, cinch audio cable, power adapter including USB cable, remote control, operating instructions
FM/RDS: 87,5 - 108 MHz	stationary radio: Yes	
Internet radio: Yes		
Aerial: DAB/FM dipole antenna		