



## DIGITRADIO 586

DAB+/FM/Internet stereo radio with CD player, Spotify Free and wireless charging function.

EAN	Colour	Item no.	Weight (Box)	Weight	Device (W x H x D)	Box
4019588039865	anthracite/silver	0000/3986	3,95 kg	3,08 kg	24 x 15 x 21,5 cm	30 x 24,5 x 25,5 cm
4019588139862	white/silver	0001/3986	3,95 kg	3,08 kg	24 x 15 x 21,5 cm	30 x 24,5 x 25,5 cm

### TOP FEATURES

DAB+ digital radio

FM radio (with RDS and PLL)

Limitless music variety via Internet radio

Audio streaming (Spotify & Bluetooth)

Oversized illuminated OLED display

CD player with MP3 playback

USB interface with charging function and mp3 playback

Control via app

Wireless charging/USB charging

### FILTER-NAVIGATION

Operating mode: Mains operation

Features: Bluetooth

Connections: F-type connector

Reception type: FM

### WLAN

WLAN: 802.11 a/b/g/n (2,4-GHz- und 5-GHz-band)

### AMBIENT OPERATING CONDITIONS

Humidity: 5 - 90 % relative air humidity (non-condensing)

Ambient temperature: 5 - 35 °C

### BLUETOOTH VERSION & PROFILE

Bluetooth version: 4,2

AVRCP (Audio Video Remote Control Profile): Yes

A2DP (Advanced Audio Distribution Profile): Yes

### CONNECTIONS

Audio in/AUX in: Yes

Headphone connection jack (3,5 mm): 1

connector for external aerial (RF connector): 1

USB: 1

### DISPLAY

Type: OLED

Size: 2,42 in

Dimmable: Yes

RadioVIS: Yes

## FUNCTIONS

MP3 playback via USB: Yes

USB charging function: Yes

CD player with MP3: Yes

Wireless charging: Yes (5 W)

## HANDLING/COMFORT

Clock: Yes

Automatic time reset following a power cut: Yes

Alarm: Yes

Sleep timer: Yes

Snooze: Yes

Remote control: Yes

Favourites programme manager Internet: 12

Favourites programme manager DAB+: 12

Favourites programme manager FM: 12

## LOUDSPEAKERS

Output performance: 20 W (RMS)

Stereo speakers: Yes

Stereo: 2 x 10 W

Equalizer: Yes

## NETWORK & COMMUNICATION

Bluetooth: Yes

## OTHER FEATURES

OSD languages: English, German, French, Polish, Italian, Dutch, Norwegian, Danish, Swedish, Finnish, Spanish, Turkish, Portuguese

## POWER CONSUMPTION

Standby: 1 W

Power consumption in standby mode with active network connection: 2 W

In operation: 36 W (max.)

## POWER SUPPLY

Nominal voltage: 230 V

Frequency: 50 Hz

Mains adapter: DC 12 V / 3000 mA

Type of power supply: external

## RADIO / RECEPTION

DAB+: 174 - 240 MHz

FM/RDS: 87,5 - 108 MHz

Internet radio: Yes

Aerial: DAB / FM telescopic antenna

## STREAMING

Bluetooth audio streaming: Yes

Spotify Free: Yes

## SUPPORTED FORMATS & CODECS

Audio-Formats: MP3, AAC

## SCOPE OF DELIVERY

DIGITRADIO 586, telescopic aerial antenna, power adapter, remote control, instruction manual