



## HD-S 261

Compact HDTV sat receiver for unencrypted digital TV and radio programs

EAN	Colour	Item no.	Weight (Box)	Weight	Device (W x H x D)	Box
4019588048140	black	0000/4814	600 g	512 g	18 x 4,4 x 13 cm	21,4 x 5,2 x 15,6 cm

### TOP FEATURES

DVB-S2 HDTV tuner

7 day EPG support

Pre-programmed for ASTRA 19° East

SCR EN50494 and EN50607

Supports audio coding format AAC

6 key operation

Compact, small housing

USB media player for video, MP3 music and picture

### FILTER-NAVIGATION

Tuner type: Single tuner

Resolution: Full HD

Features: Radio reception

Connections: Ethernet (LAN)

Reception type: Satellite (DVB-S/S2)

### AMBIENT OPERATING CONDITIONS

Humidity: 10 ... 75 %

Ambient temperature: 5 ... 35 °C

### LNB CONTROL

Vertical: 14 V

Horizontal: 18 V

Band switch: 22 kHz

Current consumption: max. 500 mA

DiSEqC: 1.0 / 1.2

### AUDIO

Clear language from ARD: Yes via DVB

### CONNECTIONS

HDMI™ (out): 1

USB: 1 (USB 2.0)

Digital electric audio output (S/PDIF): Yes

Scart: 1

Ethernet 10/100 (RJ-45): Yes

F socket: 1

### DISPLAY

SD: Yes

HD: Yes

1080p: Yes

1080i: Yes

720p: Yes

576p: Yes

576i: Yes

Type: 7-segment, 4-digit, amber

#### HANDLING/COMFORT

Media Player: Yes

Electronic Program Guide (EPG): Ja

Teletext: Yes

Clock: Yes

Remote control: Yes

#### POWER SUPPLY

Nominal voltage: 230 V

Frequency: 50 Hz

Mains adapter: internal

Effective output: max. 18 W

#### OTHER FEATURES

OSD languages: Turkish, Polish, English, Italian, French, Spanish, German, Portuguese

Total programme memory: 4.000

#### SUPPORTED FORMATS & CODECS

Video-Codecs: MPEG-2, MPEG-4, H.264

Video-Formats: MPG, MP4, TS, TS4, VOB, M2TS, AVI

JPEG: Yes

Audio-Formats: AAC, MP3, MP2

#### POWER CONSUMPTION

In operation: max. 18 W

Standby: < 1 W

#### TUNER

Tuner type: Single-Tuner

DVB-S tuner: 1

Single Cable Solution (SatCR): SCR1 = EN50494, SCR2 = EN50607

Satellite radio: Yes

Reception on: HD-TV, SD-TV, DVB-Radio

#### TUNER - SAT

Reception range: 950 ... 2.150 MHz

Viterbi rates: 1/2, 2/3, 3/4, 5/6, 7/8

DVB-S: QPSK

DVB-S: 2 ... 45

DVB-S2: 8PSK - QPSK

DVB-S2: 10 ... 31

FEC: RS, LDPC, BCH

#### SCOPE OF DELIVERY

HD-S 261 sat receiver, remote control, batteries, manual