



DIGITRADIO 372 CD BT

DAB+ / FM stereo with CD player and Bluetooth audio streaming

EAN	Colour	Item no.	Weight (Box)	Weight	Device (W x H x D)	Box
4019588051010	black	0000/5101	3,52 kg	2,78 kg	35 x 13,3 x 20 cm	42,5 x 17,5 x 24,5 cm
4019588251014	anthracite/silver	0002/5101	3,52 kg	2,78 kg	35 x 13,3 x 20 cm	42,5 x 17,5 x 24,5 cm

TOP FEATURES

DAB+ digital radio	FM radio (with RDS and PLL)	Favourites memory slots (DAB+/FM)
Integrated CD player with mp3 playback	TFT colour display (2.4")	USB interface with charging function and mp3 playback
Bluetooth audio streaming (reception)	Radio alarm timer	Sleep timer
Remote control		

FILTER-NAVIGATION

Connections: USB
Operating mode: Mains operation
Reception type: FM
Features: Bluetooth

AMBIENT OPERATING CONDITIONS

Humidity: 5 - 90 % relative air humidity (non-condensing)
Ambient temperature: 5 - 35 °C

BLUETOOTH VERSION & PROFILE

Bluetooth version: 5
AVRCP (Audio Video Remote Control Profile): Yes
A2DP (Advanced Audio Distribution Profile): Yes

CONNECTIONS

Audio in/AUX in: Yes
Headphone connection jack (3,5 mm): 1
USB: 1

DISPLAY

Type: TFT colour display (2.4")
Size: 2,4 in
Dimmable: Yes
Slide show/catSLS: Yes

FUNCTIONS

MP3 playback via USB: Yes
USB charging function: Yes
CD player with MP3: Yes

HANDLING/COMFORT

Clock: Yes

Sleep timer: Yes

Snooze: Yes

Remote control: Yes

Favourites programme manager FM: 20

Favourites programme manager DAB+: 20

OTHER FEATURES

OSD languages: English, German, French, Italian

RADIO / RECEPTION

DAB+: 174 - 240 MHz

FM/RDS: 87,5 - 108 MHz

Aerial: DAB / FM telescopic aerial

LOUDSPEAKERS

System: 10 W (RMS)

Stereo speakers: Yes

Stereo: 2 x 5 W

Equalizer (preset): Yes

POWER CONSUMPTION

Standby: <1 W

In operation: 32 W

STREAMING

Bluetooth audio streaming: Yes

NETWORK & COMMUNICATION

Bluetooth: Yes

POWER SUPPLY

Nominal voltage: 100 - 240 V

Frequency: 50 / 60 Hz

Type of power supply: internal

SUPPORTED FORMATS & CODECS

MP3: Yes

SCOPE OF DELIVERY

DIGITRADIO 372 CD BT, remote control, 2x AAA batteries, operating instructions