



## DIGITRADIO 425

DAB+/FM/Internet stereo radio with CD player, music streaming and Spotify Connect

Colour	EAN	Item no.	Weight (Box)	Weight	Device (W x H x D)	Box
anthrazit	4019588029606	0000/2960	6,55 kg	5,19 kg	40 x 19,5 x 22 cm	47,7 x 25,1 x 26 cm

### TOP FEATURES

- The DIGITRADIO 425 receives DAB+, FM and internet radio and offers 30 presets per reception type. Music enjoyment via CD player, Bluetooth reception or Spotify Connect ensures versatile entertainment.
- Thanks to dual-band Wi-Fi (2.4 and 5 GHz) for stable streams, Bluetooth 5.2, AUX-in and USB port with charging function, the radio can be connected flexibly and conveniently controlled via app, remote control or directly on the device.
- Supports MP3, AAC and MP2 as well as JPEG and PNG image formats. With a headphone jack (3.5 mm jack), mains operation and elegant design, the device fits perfectly in your living room, bedroom or study
- The 40-watt stereo speakers with equaliser ensure clear, powerful sound. The 4.3-inch colour display clearly shows station information and can be dimmed – including alarm, sleep and snooze functions

### SONSTIGES

bf\_filter\_anchluss: USB  
 bf\_filter\_austattung: App control  
 bf\_filter\_operating\_mode: Mains operation

### WLAN

WLAN: 802.11 a / b / g / n (2.4 GHz and 5 GHz band supported)

### AMBIENT OPERATING CONDITIONS

Humidity: 5 - 80 % relative air humidity (non-condensing)  
 Ambient temperature: 0 - 40 °C

### BLUETOOTH VERSION & PROFILE

Bluetooth version: 5,2  
 AVRCP (Audio Video Remote Control Profile): Yes  
 A2DP (Advanced Audio Distribution Profile): Yes

### CONNECTIONS

Audio in/AUX in: Yes  
 Headphone connection jack (3,5 mm): 1  
 USB: 1

### DISPLAY

Type: TFT colour display  
 Size: 4,3 in  
 Resolution (vertical and horizontal): 240x320  
 Dimmable: Yes  
 Slide show/catSLS: Yes

<b>FUNCTIONS</b>	<b>HANDLING/COMFORT</b>	<b>LOUDSPEAKERS</b>
USB charging function: Yes	Clock: Yes	Output performance: 40 W (RMS)
CD player with MP3: Yes	Alarm: Yes	Stereo speakers: Yes
	Sleep timer: Yes	Stereo: 2 x 20 W
	Snooze: Yes	Equalizer: Yes
	Remote control: Yes	Equalizer (preset): Yes
	Favourites programme manager FM: 40	
	Favourites programme manager DAB+: 40	
	Favourites programme manager Internet: 40	
<b>NETWORK &amp; COMMUNICATION</b>	<b>OTHER FEATURES</b>	<b>POWER CONSUMPTION</b>
Bluetooth: Yes	OSD languages: English, German, French, Polish, Italian, Dutch, Norwegian, Danish, Swedish, Finnish	Standby: <0,8 W
		Power consumption in standby mode with active network connection: <2,0 W
		In operation: 60 W
<b>POWER SUPPLY</b>	<b>RADIO / RECEPTION</b>	<b>RADIO TYPE</b>
Nominal voltage: 230 V	DAB+: 174 - 240 MHz	stationary radio: Yes
Frequency: 50 / 60 Hz	FM/RDS: 87,5 - 108 MHz	
Type of power supply: Internal features	Internet radio: Yes	
	Aerial: DAB / FM telescopic antenna	
<b>STREAMING</b>	<b>SUPPORTED FORMATS &amp; CODECS</b>	<b>SCOPE OF DELIVERY</b>
Spotify: Yes	Picture-Formats: JPEG, PNG	DIGITRADIO 425, Remote Control, 2x AAA batteries, Instruction Manual
Bluetooth audio streaming: Yes	Audio-Formats: MP2, AAC, MP3	