



DIGITRADIO 52 ASA

DAB+/FM clock radio with Bluetooth and ASA function

Colour	EAN	Item no.	Weight (Box)	Weight	Device (W x H x D)	Box
grau/weiß	4019588039827	0000/3982	875 g	501 g	14 x 6,5 x 13,8 cm	18 x 15 x 18 cm

TOP FEATURES

DAB+ digital radio and FM radio (with RDS and PLL)	Optional playback of safety messages via DAB+	Favourites memory slots (20 for DAB+ and 20 for FM)
Date and time display	Four wake-up times adjustable	Alarm via acoustic signal or radio station
Adjustable alarm frequency	Snooze and sleeptimer functions	Large LCD display with backlight
Bluetooth audio streaming (reception)		

SONSTIGES

bf_filter_operating_mode: Mains operation
 bf_filter_anschlusse: USB
 bf_filter_austattung: Alarm clock

AMBIENT OPERATING CONDITIONS

Humidity: 5 - 80 % relative air humidity (non-condensing)
 Ambient temperature: 0 - 40 °C

BLUETOOTH VERSION & PROFILE

Bluetooth version: 5
 A2DP (Advanced Audio Distribution Profile): Yes

CONNECTIONS

Headphone connection jack (3,5 mm): 1
 USB: 1

DISPLAY

Type: LCD
 Size: 4,2 in
 Dimmable: Yes (automatisch mit Lichtsensor)

FUNCTIONS

USB charging function: Yes

HANDLING/COMFORT

Clock: Yes

Automatic time reset following a power cut: Yes

Alarm: Yes

Sleep timer: Yes

Snooze: Yes

Favourites programme manager DAB+: 20

Favourites programme manager FM: 20

POWER CONSUMPTION

Standby: <1 W

In operation: 11 W

RADIO TYPE

stationary radio: Yes

LOUDSPEAKERS

Output performance: 3 W (RMS)

Mono speakers: Yes

Equalizer: Yes

POWER SUPPLY

Nominal voltage: 230 V

Frequency: 50 / 60 Hz

Mains adapter: DC 5.0 V / 2000 mA

Type of power supply: external

OTHER FEATURES

OSD languages: English, German, French, Italian, Dutch, Norwegian, Spanish

RADIO / RECEPTION

DAB+: 174 - 240 MHz

FM/RDS: 87,5 - 108 MHz

Aerial: DAB/FM aerial

SCOPE OF DELIVERY

DIGITRADIO 52 ASA, power adapter, instruction manual