


# LEVELMETER LED

For quick adjustment of your satellite antenna

| EAN | Colour | Item no. | Weight (Box) | Weight | Device (W x H x D) | Box |
|---|---|---|---|---|---|---|
| 4019588330450 | yellow/silver | 0003/3045 | 106 g | 106 g | 8,5 x 4,8 x 3,1 cm | 9,5 x 13,6 x 5 cm |

## TOP FEATURES

- LED level indicator
- Input sensitivity adjustable
- 22 kHz LED for high or low band indication
- Frequency range: 950 - 2400 MH
- Transmission loss: less than 10 dB
- Connectors: F-socket

## FREQUENCY RANGE

- Digital & analogue satellite: 950 ... 2.400 MHz

## GENERAL CHARACTERISTICS

- Input impedance: 75 Ω
- Display: LED level indicato (7 Elemente)

## SCOPE OF DELIVERY

- LEVELMETER LED